

This Projector supports the following Crestron Electronics controller and software commands.

| Category | Name | Join Type | Join Numbers | | | |
|--------------------------|-----------------------------|-----------|--------------|--------|----------------|--------|
| | | | RoomView | | Control System | |
| General Info | Online | Digital | 1 | In | 1 | In |
| | Help Request | Serial | 1 | In/Out | 1 | In/Out |
| | Device ID string | Serial | 40 | In | 40 | In |
| Power | Power On | Digital | 5 | In/Out | 5 | In/Out |
| | Power Off | Digital | 6 | In/Out | 6 | In/Out |
| | Status Message | Serial | 5001 | In | 11 | In |
| Emergency Message | Emergency Alert | Serial | 22 | In/Out | 22 | In/Out |
| | Emergency Message | Analog | 22 | In/Out | 22 | In/Out |
| | Emergency Message Supported | Digital | 22 | In | 22 | In |
| Lamp | Lamp hours Integer | Analog | 2 | In | 2 | In |
| Picture | Brightness Level | Analog | 5002 | In | 32 | In |
| | Contrast Level | Analog | 5003 | In | 33 | In |
| | Brightness Plus | Digital | 5109 | In/Out | 119 | In/Out |
| | Brightness Minus | Digital | 5110 | In/Out | 120 | In/Out |
| | Contrast Plus | Digital | 5111 | In/Out | 121 | In/Out |
| | Contrast Minus | Digital | 5112 | In/Out | 122 | In/Out |
| Audio | Volume | Analog | 5012 | In | 42 | In |
| | Volume Up | Digital | 5115 | In/Out | 125 | In/Out |
| | Volume Down | Digital | 5116 | In/Out | 126 | In/Out |
| | Mute On | Digital | 5117 | In/Out | 127 | In/Out |
| | Mute Off | Digital | 5118 | In/Out | 128 | In/Out |
| Network | IP Address | Serial | 5040 | In | 50 | In |
| | Subnet Mask | Serial | 5041 | In | 51 | In |
| | Default Gateway | Serial | 5042 | In | 52 | In |
| | DNS Server | Serial | 5043 | In | 53 | In |
| | Mac Address | Serial | 5044 | In | 54 | In |
| | Control System IP Address | Serial | 5045 | In | 55 | In |
| | Control System IP ID | Serial | 5046 | In | 56 | In |
| | Control System Port | Serial | 5047 | In | 57 | In |
| | DHCP Enable | Digital | 5210 | In | 220 | In |
| | DHCP Disable | Digital | 5211 | In | 221 | In |
| Source | Source Select 1 | Digital | 5070 | In/Out | 80 | In/Out |
| | Source Select 2 | Digital | 5071 | In/Out | 81 | In/Out |
| | Source Select 3 | Digital | 5072 | In/Out | 82 | In/Out |
| | Source Select 4 | Digital | 5073 | In/Out | 83 | In/Out |
| | Source Select 5 | Digital | 5074 | In/Out | 84 | In/Out |

| | | | | | | |
|---------------------------|-------------------------|---------|------|--------|-----|--------|
| | Source Select 6 | Digital | 5075 | In/Out | 85 | In/Out |
| | Source Select 7 | Digital | 5076 | In/Out | 86 | In/Out |
| | Source Select 8 | Digital | 5077 | In/Out | 87 | In/Out |
| | Source Select 9 | Digital | 5078 | In/Out | 88 | In/Out |
| | Source Select 10 | Digital | 5079 | In/Out | 89 | In/Out |
| | Source 1 Name Text | Serial | 5070 | In/Out | 80 | In/Out |
| | Source 2 Name Text | Serial | 5071 | In/Out | 81 | In/Out |
| | Source 3 Name Text | Serial | 5072 | In/Out | 82 | In/Out |
| | Source 4 Name Text | Serial | 5073 | In/Out | 83 | In/Out |
| | Source 5 Name Text | Serial | 5074 | In/Out | 84 | In/Out |
| | Source 6 Name Text | Serial | 5075 | In/Out | 85 | In/Out |
| | Source 7 Name Text | Serial | 5076 | In/Out | 86 | In/Out |
| | Source 8 Name Text | Serial | 5077 | In/Out | 87 | In/Out |
| | Source 9 Name Text | Serial | 5078 | In/Out | 88 | In/Out |
| | Source 10 Name Text | Serial | 5079 | In/Out | 89 | In/Out |
| | Current Source | Serial | 5010 | In | 20 | In |
| Password | Admin Password Enable | Digital | 5216 | In/Out | 226 | In/Out |
| | Admin Password Disabled | Digital | 5217 | In/Out | 227 | In/Out |
| Info - Advanced | Projector Name | Serial | 5050 | In/Out | 60 | In/Out |
| Picture - Advanced | Menu | Digital | 5150 | In/Out | 160 | In/Out |
| | Up | Digital | 5151 | In/Out | 161 | In/Out |
| | Down | Digital | 5152 | In/Out | 162 | In/Out |
| | Left | Digital | 5153 | In/Out | 163 | In/Out |
| | Right | Digital | 5154 | In/Out | 164 | In/Out |
| | Exit | Digital | 5155 | In/Out | 165 | In/Out |
| | Enter | Digital | 5156 | In/Out | 166 | In/Out |
| | AV Mute Off | Digital | 5190 | In/Out | 200 | In/Out |
| | AV Mute On | Digital | 5191 | In/Out | 201 | In/Out |