

Appendix C:

Troubleshooting / Other Information

Troubleshooting	78
Specifications	79

Troubleshooting

The following provides information on what to do whenever you experience problems with data analyzer operation.

Problem:

Data analyzer power does not turn on and nothing appears on its display.

Possible Causes and Recommended Actions:

- No batteries are loaded or the (+)/(-) ends of the batteries are facing in the wrong directions. Make sure that batteries are loaded correctly.
- Low battery power. Replace batteries.
- Check the AC adaptor if you are using it to power the data analyzer.

Problem:

Cannot communicate with a connected CFX-9850G or CFX-9800G.

Possible Causes and Recommended Actions:

- Check to make sure that the data analyzer is turned on and that the data communication cable is pushed in as far as it will go on both units.
- Press the data analyzer's [HALT] key to clear it.
- Check to make sure that the CFX-9850G or CFX-9800G program you are using is written correctly. If you keep getting an error message, see page 62.
- The data analyzer cannot communicate with the CFX-9850G or CFX-9800G if it is in the Multimeter Mode or Internal Mode. Change to the Communications Mode and try again.

Specifications

Model:	CASIO EA-100 Data Analyzer
Power Supply:	Four AA-size batteries (LR06 (AM3) or R6P (SUM-3)) or optional AC adaptor (AD-A60024)
Power Consumption:	1.5W
Battery Life:	LR06 (AM3): Approximately 12 hours (Continuous Multimeter Mode) / Approximately two years (when is left with power off) R6P (SUM-3): Approximately 7 hours (Continuous Multimeter Mode) / Approximately two years (when is left with power off)
Auto Power Off:	Approximately 10 minutes after last key operation. See page 11 for information on conditions under which Auto Power Off is disabled.
Operating Temperature:	0°C to 40°C (EA-100) The tip of the temperature probe can be used in temperatures ranging from -20°C to 130°C.
Dimensions:	86(W) × 214.5(D) × 32.2(H) mm
Weight:	305.5g (including batteries)
Standard Accessories:	Light Probe (CDAP-01); Temperature Probe (CDAP-02); Voltage Probe (CDAP-03); four AA-size batteries (R6P (SUM-3)); Data Communication Cable (SB-62); Carrying Case; User's Guide



Batterij niet weggooien,
maar inleveren als
KCA



CASIO ELECTRONICS CO., LTD.
Unit 6, 1000 North Circular Road,
London NW2 7JD, U.K.